

Coilcraft S-Parameter Data for RF Surface Mount Inductors BCR Series Broadband Conical Inductors

Version BCR May, 2024 Coilcraft, Inc.


Coilcraft two-port S-parameter data files are based on empirical measurements of Coilcraft Inductors. The data files are used as "black box" descriptions, thus reducing complexity in circuit modeling.

The data files represent de-embedded measurements. Effects due to customer circuit board traces, board materials, ground planes, or interactions with other components are not included and can have a significant effect when comparing the S-parameters to measurements of the inductors using typical production verification instruments and fixtures.

Since data sheet specifications are based on typical production measurements, and the S-parameter models are based on de-embedded measurements as described below, the S-parameter model results may be different from the data sheet specifications.

S-parameter modeling method

The measurements for this series were made with the inductor mounted as shown in the shunt to ground configuration shown below. The valid frequency range is **50 MHz to 40 GHz**. Ports 1 and 2 are both 50 Ohms characteristic impedance.



The S-parameters were generated using a circuit simulation software program to de-embed the test fixture. This method results in s-parameters that represent as closely as possible the typical frequency-dependent behavior of the inductor within the valid frequency range.

S-parameter file description.

All of the S-parameter data files are in the TouchStone format. The following is a typical file header of a two-port file:

```
!freq-unit  param-type  data-format  keyword  impedance-ohms
# GHz      S          DB          R          50
!-----
!Freq      DBS11  AngS11  DBS21 AngS21  DBS12  AngS12  DBS22  AngS22
....
```


Coilcraft S-Parameter Data for RF Surface Mount Inductors BCR Series Broadband Conical Inductors

The first line (header) describes the frequency units, parameter type, measurement format and characteristic impedance of the measurement (50 Ohms).

The first column is the frequency in GHz. The next columns are the S-parameters as described in the column headings.

Using the s-parameters in a simulation

Broadband conical inductors are typically used in a bias tee configuration (to bias an amplifier). Because these S-parameters were measured shunt to ground, they cannot be used for simulating a DC bias tee. Contact Modelithics for series measured substrate dependent S-parameters.



Equivalent circuit of a bias tee

Disclaimer

Coilcraft makes every attempt to provide accurate measurement data and software, representative of our components, in a usable format. Coilcraft, however, disclaims all warrants relating to the use of its data and software, whether expressed or implied, including without limitation any implied warranties of merchantability or fitness for a particular purpose. Coilcraft cannot and will not be liable for any special, incidental, consequential, indirect or similar damages occurring with the use of the data and/or software.